

RS232 Code Liste

PFY-HHUD70Tx86			
Command	ASCII	HEX	Connection Protocol
HDMI input	AV_HDMI	41 56 5F 48 44 4D 49	Baud Rate
DP input	AV_DP	41 56 5F 44 50	Data Bit
USB-C input	AV_TYPEC	41 56 5F 54 59 50 45 43	Stop Bit
Auto Switch On/Off	FE 60	46 45 20 36 30	Parity
			Connection Port

PFY-HUD70Tx86				
Command	ASCII	HEX		Connection Protocoll
HDMI input	HDMI.			Baud Rate
DP input	DP.			Data Bit
USB-C input	TYPEC.			Stop Bit
Auto Switch On/Off	AUTO.			Parity
Disconnect Input	CLOSE.			Connection Port
Switch Manual	MANUAL.			
Reboot device	REBOOT.			
Set EDID PFY	EDIDPFY.			
Set EDID Bypass	EDIDBYPASS.			
Set EDID to 2k	EDID2K.			
Set EDID to 4k	EDID4K.			
Send Ctrl 1 Command	Ctrl1.			
Send Ctrl 2 Command	Ctrl2.			
Send Ctrl 3 Command	Ctrl3.			
Send Ctrl 4 Command	Ctrl4.			
Send Ctrl 5 Command	Ctrl5.			
Send Ctrl 6 Command	Ctrl6.			
Send Ctrl 7 Command	Ctrl7.			
Send Ctrl 8 Command	Ctrl8.			
Send Ctrl 9 Command	Ctrl9.			
Send Ctrl 10 Command	Ctrl10.			

Settings
115200
8
1
None
RS232

Settings
115200
8
1
None
USB-C